



Fuse Block Range

There's nothing more annoying than having your power system hindered by bothersome spaghetti cords. The Baintech Fuse Blocks, provide a safe and easy-to-use hub for all your fuses. They even come with labels to help you keep everything organised.

Baintech's Fuse Blocks will keep your system protected and help you make sure all your connections are correctly and safely fused. Available for use with 6 or 12 appliances, the Baintech Fuse Blocks are a great way to simplify your power system.

Features

- ✓ 100 amps maximum per fuse block
- ✓ 30 amps maximum per individual fuse
- ✓ Common negative and common positive
- ✓ Provision for holding 2 spare fuses
- ✓ Accepts ATO and ATC standard fuses
- ✓ Clear cover made from polycarbonate
- ✓ Cover satisfies ABYC/USCG requirements for insulation
- ✓ Base made from reinforced polycarbonate
- ✓ Suitable for 12 or 24 Volt system



Specifications

Model	BTFB6	BTFB12
Max Amps Per circuit	30 Amperes	30 Amperes
Max Amps Per Block	100 Amperes	100 Amperes
Fuse outlets	6	12
Max Voltage	32V DC	32V DC
Recommended Wire Size (+/- Feed)	up to 35mm ²	up to 35mm ²
Recommended Wire Size (Individual circuits)	up to 10mm ²	up to 10mm ²
Recommended Torque	#8 Screw 2 NM #8 Stud 3 NM	#8 Screw 2 NM #8 Stud 3 NM
Max Ambient Temperature	0 - 50°C	0 - 50°C
Dimensions	124.31 x 84.20 x 38.55mm	164.39 x 84.20 x 38.57mm